

# CBB61 型交流电动机电容器

## CBB61 Type AC Motor Capacitor

SINO-U.S JOINT-VENTURE ZHEJIANG  
JIUKANG ELECTRIC CO.,LTD

专注才能更成功

www.jiukang.com



### 特点 Features

体积小、电气性能稳定、具有自愈性能、环氧树脂灌封壳。

Small size, reliable electrical performance, Self-healing, canned epoxy impregnant structure.

### 用途 Applications

适用于频率50Hz(60Hz)的交流电源供电的单相电机起动和运行。

Applied to starting and better working of single-phase motor in 50Hz(60Hz) AC electric power system.

### 规格尺寸 Specification and Dimensions

额定电压 (VAC)	标称容量 ( $\mu F$ )	尺寸Size(mm)			备注 Note
		L	B	H	
450	1	31	17	27	底部 单耳 bottom lug
		37	14	24	
	1.5	37	18	28	
		48	18	29	
	2	38	18	29	
		48	18	29	
	2.5	47	18	34	
		38	21	31	
	3	47	18	34	
		47	22	34	
	3.5	47	18	34	
		47	22	34	
	4.5	48	26	38	
		48	26	38	
	6	48	26	38	
48		26	38		
10	48	34	52	方壳 square enclosure	
	48	34	52		

注: 1、引出端为187#(250#)单(双)焊片或镀锡铜线

Terminal form is 187#(250#) single (double) soldering flat picc(s) or copper wire coated with tin.

2、其它尺寸系列, 可根据用户需要商定。

Other dimension series can be ensured according to customer s request.

### 外形尺寸 Overall Dimension

